



HOW TO INSTALL

Installing your BullShooter Galaxy 3 dartboard is a manageable task, especially with the right guidance. Here's a concise step-by-step overview to assist you:



1. Unpack and Inspect

- Carefully remove the dartboard from its packaging.
- Ensure all components are present and undamaged, including the cabinet, monitor, darthead, power cord, and any accessories. arachnid360.com

2. Position the Dartboard

- Place the dartboard against a sturdy wall.
- Attach the thread studs to the dartboard base, then place the top cabinet onto the base.
- Open the top of cabinet once it is placed on the base, and secure the 4 nuts onto the base threads in the four corners of the top cabinet.
- Ensure the area allows for at least 10 ft from the front of the dartboard to allow for correct throw line placement.

3. Connect Power and Network

- Plug the power cord into a grounded outlet.
- If utilizing network features, connect the Ethernet cable, or Wifi connection to your network source.

4. Power On and Configure

- Turn on the dartboard using the power switch.
- Follow on-screen prompts to set up language preferences, date/time, and network settings.
- Test the darthead and monitor functionality to ensure proper operation.

For detailed instructions, refer to the Galaxy 3 Plus Operator's Manual. If you need assistance with specific features like League Leader setup or remote play, feel free to ask!

REMOTE PLAY

Remote Play on an BullShooter dartboard lets players compete live against others at different locations using internet-connected Galaxy 3 dartboards. The system syncs game data in real-time, allowing for live scoring, video interaction, and seamless remote matches through LeagueLeader.

Here's a simplified guide to set up **Remote Play** on your **BullShooter Galaxy 3** dartboard:

1. Connect to the Internet

- Plug in an Ethernet cable or connect to Wi-Fi.
- Make sure the board has internet access.

2. Go into Service Mode

- Open the dartboard and press the Service Button inside.
- Go to **Communications > LeagueLeader Setup**.

3. Enter LeagueLeader Info

- Type in your **FTP password**.
- Return to Communications Screen and press **Perform Update** to test the connection.

4. Enable Remote Play Online

- Log in to **LeagueLeader.com** on your internet connected device.
- Go to your location settings under **MASTER** select the location Modify, and enter the Boards MAC address. Check the box labeled **Remote Play** after the MAC address is entered. Press the **OK** button after those steps are done.

ONSITE DART TRAINING AVAILABLE!

Contact your rep or call (800) 435-8319 to schedule your session.

- Now on the Home Screen of **LeagueLeader.net** select the **Generate Files** button on the far left of the screen. In the **Generate Files** screen make sure all settings look correct then click the **OK** button. You are now done setting up the board from your internet connected device.
- Final step for getting your BullShooter dartboard online is to make sure the board is online with all it's features. Have the dartboard make a call either by going into the service menu, and perform update or alternatively you can press the triple 20 segment 6 times to make a call.
- Your brand new dartboard is now connected to the World! Enjoy!

5. Start Playing Remotely

- On the dartboard main screen, select **Remote Play**.
- Choose your number of players, and use the QR code on this screen to log into your **Bullshooter Live** account using the **Bullshooter Live App** on your mobile device!
- Now select which of the exciting game types you want to play in **Remote Play**, now find an opponent and play away!
- The board connects and the game starts!

